

ACTION	BUTTON
BASIC INSTRUCTION COMMANDS	
Power on	Hold <i>Answer</i> for 3 seconds.
Power off	Hold <i>Answer</i> for 5 seconds.
Volume up	Press <i>Up</i> once.
Volume down	Press <i>Down</i> once.
VOICE CALL	_
Activate Phone pairing	Hold <i>Up</i> & <i>Down</i> for 2 seconds.
Pick up incoming call	Press Answer once.
End call in progress	Hold <i>Answer</i> for 2 seconds.
Reject incoming call	Hold <i>Answer</i> for 2 seconds.
Voice dial	Hold Answer & Down for 2 seconds.
Last number redial	Hold Answer & Up for 2 seconds.
Swap call	Press Answer once.
MUSIC STREAMING	
Play	Press Answer 2 times.
Stop	Press Answer 1 times.
Fast forward track	Press <i>Up</i> button 2 times.
Backtrack	Press <i>Down</i> button 2 times.
INTERCOM	
Pairing Two Units	Unit 1, from the off position, hold <i>Answer</i> and <i>Down</i> for 3 seconds. On Unit number 2; from the off position, press/hold the answer and Up button for 3 seconds. When Unit 1 turns to a double blue blink, press the <i>Answer</i> button on the second unit to indicate you are done pairing. Reboot both to complete/save the pairing process.
Pairing Three or More Units	Unit 1, from the off position, hold <i>Answer</i> and <i>Down</i> for 3 seconds. On Unit number 2, from the off position, press/hold the answer and Up button for 3 seconds. Unit 1 turns to a double blue blink, start the third unit, press/hold the answer and Up button for 3 seconds. When Unit 2 begins a double blue blink you can either start unit 4 with the same protocol as unit 3, or end the processes by hitting the Uclear Button on the last unit connected to indicate you are done pairing. Reboot all units to complete/save the pairing process
Connect intercom	Hold <i>Up</i> for 2 seconds.
Disconnect intercom	Hold <i>Down</i> for 2 seconds.
PRIVATE INTERCOM (all intercom units must be connected) *for HBC200 series only	
Enable pairing	Press <i>Answer</i> and <i>up</i> button.
Stop pairing	Press <i>Answer</i> on one of the units.
Switch to common channel	Press Answer button once, you will hear single beep tone.
Switch to private channel	Press <i>Answer</i> button once, you will hear double beep tone.
CROSS BRAND INTERCOM	
Pairing	 Setup other brand device in mobile phone pairing mode first. Power on the UCLEAR unit and keep holding the <i>Answer</i> button for 10 seconds.
Connect intercom	Hold <i>Up</i> for 2 seconds.
Disconnect intercom	Hold <i>Down</i> for 2 seconds.
MUSIC SHARING *firmware 2.13+	
Pairing as first unit	UCLEAR unit must be turned on first. Press Answer and down button twice.
Paring as second unit	UCLEAR unit must be turned on first. Press Answer and up button twice.